

1. Attach the mounting bracket to the junction box with the included unfinished mounting screws. Utilize the long curved slots on the mounting bracket.
2. Prepare the White and Black wires on the adapter by pre-bending the wires so they are positioned in the middle of the LA-18 adapter and aligned with the opening in the middle of the mounting plate.

NOTE: This step is required to avoid unnecessary contact with mounting bracket and potential damage to the wires.

3. Connect the LA-18 adapter wires to the 120V supply wires (black to black, white to white, green to ground) with wire nuts.
4. Carefully feed wires through the opening on the mounting bracket and into the junction box while putting the adapter into place.
5. Attach the LA-18 Mono-Point adapter to the universal mounting plate using (2) painted Philips head screws attached.

IMPORTANT SAFETY INSTRUCTIONS:

- Read all the instructions before installation. Save instructions for later use.
- Turn off the power at fuse or circuit breaker box before installation or any maintenance work.
- Wear rubber soled shoes and work on a sturdy wooden or non-conductive ladder.
- Product must be mounted in locations and at heights in compliance with National Electrical Code and local building codes. For indoor use only.
- Do not exceed the nominal supply voltage or amperage ratings.
- Installing contrary to instructions may cause unsafe conditions.
- **Warning:** Risk of fire. Most dwellings built before 1985 have supply wire rated at 60°C. Consult a qualified electrician before installation.
- To avoid hazards to children, account for all parts and properly dispose of all packing materials.
- Call the Technical Support department at ConTech Lighting with any installation questions.