

For the ConTech Lighting Metro Single or Double Wall Sconce: **WS20**

INSTALLATION PROCEDURES

This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

1. Turn off power
2. Loosen the two (2) Set Screws and remove the universal mounting plate.
3. Attach mounting bracket to the outlet box with the screws provided. **NOTE:** Driver module mounts facing inside of junction box
4. Make the wire connections. Connect the white wire to neutral and the black wire to line voltage. Connect the Green/Yellow wire to ground.
5. Position and level fixture over mounting plate and re-secure two (2) set screws. **NOTE:** Double Metro Sconce can mount in either vertical or horizontal orientation.

IMPORTANT SAFETY INSTRUCTIONS:

- Read all the instructions before installation. Save instructions for later use.
- THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED
- MIN 60°C SUPPLY CONDUCTORS
- Turn off power at fuse or circuit breaker box before installation or before doing any maintenance work.
- Product must be grounded to avoid potential electric shock and any other potential hazards.
- Product must be mounted in locations and at heights and in a manner consistent with its intended use, and in compliance with National Electrical Code and local codes. Use of accessory equipment is not recommended.
- Installing contrary to instructions may cause unsafe conditions.
- Warning: Risk of fire. Consult a qualified electrician before installation.
- To avoid hazards to children, account for all parts and properly dispose of all packing materials.
- Call the Technical Support department at ConTech Lighting with any installation questions: 847.559.5500.

All specifications subject to change without notice.